?

APC Smart-UPS X 1500VA Rack/Tower LCD 230V



APC Smart-UPS X 1500VA Rack/Tower LCD 230V

???????: ??? ????????
????:

??????? ?????? ?? ????? ??????

?????????????: APC

????????

APC Smart-UPS X 1500VA Rack/Tower LCD 230V

Output

Output Power Capacity 1200 Watts/ 1500 VA

Nominal Output Voltage 230V

Output Frequency (sync to mains) 47 - 63 Hz

Topology Line Interactive

Waveform Type Sine wave

Output Connections

(8) IEC 320 C13

(2) IEC Jumpers

Input

Nominal Input Voltage 230V

Input Frequency 50/60 Hz +/- 3 Hz (auto sensing)

Input Connections

IEC-320 C14

Cord Length 1.83 meters

Input voltage range for main operations 160 - 285V

Input voltage adjustable range for mains operation 151 - 302V

Input Breaker Capacity 20.0 A

Communications & Management

Interface Port(s) SmartSlot,USB

Available SmartSlot™ Interface Quantity 1

Control panel Multi-function LCD status and control console

Audible Alarm Alarm when on battery : distinctive low battery alarm : overload continuous tone alarm

Emergency Power Off (EPO) Yes

Surge Protection and Filtering

Surge energy rating 645 Joules

Filtering Full time multi-pole noise filtering : 5% IEEE surge let-through : zero clamping response time : meets UL 1449

Physical

Maximum Height 89.00 mm

Maximum Width 432.00 mm

Maximum Depth 490.00 mm

Rack Height 2U

Net Weight 24.82 KG

Shipping Weight 30.00 KG

Shipping Height 246.00 mm

Shipping Width 589.00 mm

Shipping Depth 620.00 mm

Color Black

Units per Pallet 16.00

Environmental

Operating Environment 0 - 45 °C

Operating Relative Humidity 0 - 95%

Operating Elevation 0-3000 meters

Storage Temperature -15 - 45 °C

Storage Relative Humidity 0 - 95%

Storage Elevation 0-15000 meters

Audible noise at 1 meter from surface of unit 40.00 dBA

Online Thermal Dissipation 133.00 BTU/hr

Conformance

Regulatory Approvals C-tick,CE,EN 50091-1,EN 50091-2,VDE

Standard Warranty 3 years repair or replace (excluding battery) and 2 year for battery

Environmental Compliance RoHS 7b Exemption,REACH: Contains No SVHCs

??????

??? ??????? ?? ???? ??????.